

Solid shaft with clamping flange, optical multiturn encoder 21 bit ST / 16 bit MT

Article number: 11267453

Overview

- Encoder multiturn / bus cover
- Optical sensing method
- Resolution: singleturn 21 bit (default: 13 bit), multiturn 16 bit (default: 16 bit)
- Total resolution up to 31 bit
- Clamping flange
- Interface: CANopen®
- Internal continuity check with diagnostic information by bus
- Maximum resistant against magnetic fields
- Gear factor adjustable via numerator / denominator
- Dynamic PDO-mapping



Picture similar

Technical data				
Technical data - electrical ratings		Technical data - electrical ratings		
Voltage supply	830 VDC	Status indicator	DUO-LED integrated in bus cover	
Reverse polarity protection	Yes	Approval	UL approval / E217823	
Consumption w/o load	≤100 mA (24 VDC)	Technical data - mechanical design		
Initializing time typ.	180 ms after power on	Size (flange)	ø58 mm	
Interface	CANopen®	Shaft type	ø10 x 20 mm, solid shaft with flat	
Function	Multiturn	Flange	Clamping flange	
Profile conformity	CANopen® CiA 301 V4.2.0	Protection EN 60529	IP 65 / IP 67 (with shaft seal)	
Node-ID	Adjustable via rotary switches in bus cover or interface	Operating speed	≤6000 rpm (+25 °C)	
		Starting acceleration	≤1000 U/s²	
Steps per revolution	≤2097152 / 21 bit	Starting torque	≤0.04 Nm (+25 °C, IP 65 / IP 67)	
Number of revolutions	≤65536 / 16 bit	Admitted shaft load	≤40 N axial ≤80 N radial	
Absolute accuracy	±0.01 °			
Sensing method	Optical	Material	Housing: aluminium Flange: aluminium Bus cover: zinc die-cast Shaft: stainless steel	
Code	Binary			
Interference immunity	EN 61000-6-2			
Emitted interference	EN 61000-6-3	Operating temperature	-25+85 °C (see general information)	
Programmable parameters	Steps per revolution Number of revolutions Preset Scaling Rotating direction Gear factor	Relative humidity	95 % non-condensing	
		Resistance	EN 60068-2-6	
		Resistance	Vibration ±0.75 mm - 10-58 Hz, 10 g - 58-	
			2000 Hz	
			EN 60068-2-27	
Diagnostic function	Position or parameter error Multiturn sensing Operating hour counter		Shock 200 g, 3 ms	
		Weight approx.	550 g	
		Connection	Cable gland	

Solid shaft with clamping flange, optical multiturn encoder 21 bit ST / 16 bit MT

Article number: 11267453

General information

Self-heating correlated to installation and ambient conditions as well as to electronics and supply voltage must be considered for precise thermal dimensioning. Operating the encoder close to the maximum limits requires measuring the real prevailing temperature at the encoder flange.

Terminal assignment		
Signals	Description	
GND	Ground connection relating to UB	
UB	Voltage supply	
CAN_H	CAN bus signal (dominant High)	
CAN_L	CAN bus signal (dominant Low)	

Terminals of the same significance are internally connected and identical in their functions. Max. load on the internal terminal connections UB-UB and GND-GND is 1 A each.

Baud rate




Baud rate	Dip switch position			
	1	2	3	
10 kBit/s*	OFF	OFF	OFF	
20 kBit/s*	OFF	OFF	ON	
50 kBit/s	OFF	ON	OFF	
125 kBit/s	OFF	ON	ON	
250 kBit/s	ON	OFF	OFF	(default)
500 kBit/s	ON	OFF	ON	
800 kBit/s	ON	ON	OFF	
1 MBit/s	ON	ON	ON	

Note:

The baud rate 100 kBit/s can only be configured via CANopen object (2100h).

View inside bus cover



Cable: 1, 2 = ø8-10 mm (-40-85 °C) / ø5-9 mm (-25-85 °C) Cable: $3 = \emptyset 4.5-6 \text{ mm } (-40-85 ^{\circ}\text{C}) / \emptyset 3-6 \text{ mm } (-25-85 ^{\circ}\text{C})$

Terminating resistor




ON = final user OFF = user X

Default: OFF

CANopen® features	
Operating modes	Time-driven (Event-Time) Synchronously triggered (Sync)
Node Monitoring	Heartbeat Node guarding
Programmable parameters	Scaling Rotating direction Electronic gear function (adjustable via numerator / denominator) MUR (Measuring Units per Revolution) TMR (Total Measuring Range) Speed configuration Operating modes
Diagnosis	Multiturn sensing Position error Battery level
Functions	Electronic gear function Dynamic PDO mapping Preset value

LED status

Node-ID



Defined by rotary switch (Node-ID 01 to 99). If a higher node ID is required use the CANopen configuration.

If the rotary switch is set to 00, the Node-ID and the baud rate can be configured via the CANopen objects 2101h (Node-ID) and 2100h (baud rate).

Example: 23 Default: 00

^{*} not supported



Solid shaft with clamping flange, optical multiturn encoder 21 bit ST / 16 bit MT Article number: 11267453

Dimensions 79 10 20 ø10f7 33 15 60 ø36f8 ø53 ø58 63 M3x7 0 ø48 ±0.2 18

EN580C.ML-SC - cable gland



Solid shaft with clamping flange, optical multiturn encoder 21 bit ST / 16 bit MT Article number: 11267453

Accessories			
Mounting accessories			
11065545	Set of eccentric fixings type A		
10141255	Adaptor plate for clamping flange to convert into synchro flange		
10125051	Mounting adaptor		
10141133	Spring washer coupling (D1=10 / D2=10)		